
Topic / Issue: Resetting the Managed Media Converters to factory default- RC-2002Sx / RC-2201Sx


Written By: Scott Young

How to reset the Managed Media Converters to their factory default settings

1. Connect the supplied serial cable to your PC and the Media Converter.
2. Start a terminal emulation program such as Hyperterminal and create a new connection with the following settings:
 - 57600
 - 8
 - None
 - 1
 - No flow control.
3. Hit Enter to activate the Login Menu .
4. Once the login menu has appeared hit "CTRL (left of the keyboard)" + space bar + "Backspace", simultaneously.
5. Key in "sh" in the user name, but note that only "h" will appear. Hit "Enter"



```
Gigabit Managed Media Converter - RC-2201
```



```
Login Menu
Username: h
Password:
```

-
6. A hash "#" should appear, type in "default".
-

```
Gigabit Managed Media Converter - RC-2201
```

```
# default_
```

```
  Login Menu
  Username: h
  Password:
```

7. Once the converter has loaded the default settings, the hash symbol will reappear.

```
Gigabit Managed Media Converter - RC-2201
```

```
# default
== Force Default ==
config size: 25240 bytes.(NEW)
#
```

```
  Login Menu
  Username: h
  Password:
```

8. Now turn the unit off then back on. The login screen will now appear.

You will now be able to login using the default username and password (admin), from either the serial interface or the web management.

Summary:
(If required)